

Включить SHR в DSM 6.2

Intuitive & fast volume creation

SHR combines different sizes of hard disk to give you the optimal volume space




SHR удален из DSM 6. Если вы хотите вернуть SHR, вы можете сделать это, отредактировав файл synoinfo.conf.

Отредактируйте файл:

```
sudo vi /etc.defaults/synoinfo.conf
```


включаем SSH

Панель управления → Терминал и SNMP → Включить службу SSH → Применить




Запускаем программу [PuTTY](#)

Вводим IP адрес нашего NAS и порт, указанный нами в закладке «Терминал и SNMP» → клавиша «Соединиться»



Вводим наш логин от NAS → пароль от нашего NAS →



клавиша «ENTER»




```
192.168.1.184 - PuTTY
login as: vladPolSKIY
vladPolSKIY@192.168.1.184's password:
Could not chdir to home directory /var/services/homes/vladPolSKIY: No such file or directory
vladPolSKIY@NAS-A:/$
```

sudo -i




```
192.168.1.184 - PuTTY
login as: vladPolSKIY
vladPolSKIY@192.168.1.184's password:
Could not chdir to home directory /var/services/homes/vladPolSKIY: No such file or directory
vladPolSKIY@NAS-A:/$ sudo -i
```

клавиша «ENTER» → свой пароль → клавиша «ENTER»



```
192.168.1.184 - PuTTY
login as: vladPolSKIY
VladPolSKIY@192.168.1.184's password:
could not chdir to home directory /var/services/homes/vladPolSKIY: No such file
or directory
VladPolSKIY@NAS-A:/$ sudo -i
Password:
```

vi /etc.defaults/synoinfo.conf



```
192.168.1.184 - PuTTY
unique="synology_broadwell_3617xs"
company_title="Synology"

# system options
timezone="Pacific"
language="def"
maillang="enu"
codepage="enu"
defquota="5"
defshare="public"
defgroup="users"
defright="writeable"
configured="no"
pswdprotect="no"
autoblock_expiredday="0"
autoblock_attempts="0"
autoblock_attempt_min="0"
support_syno_hybrid RAID = «yes»
supportphoto="yes"
support_download="yes"
supportquota="yes"
supportitunes="yes"
supportddns="yes"
"/etc.defaults/synoinfo.conf" 352L, 8306C 1,1 Top
```

i

```
192.168.1.184 - PuTTY
unique="synology_broadwell_3617xs"
company_title="Synology"

# system options
timezone="Pacific"
language="def"
maillang="enu"
codepage="enu"
defquota="5"
defshare="public"
defgroup="users"
defright="writeable"
configured="no"
pswdprotect="no"
autoblock_exprieday="0"
autoblock_attempts="0"
autoblock_attempt_min="0"
support_syno_hybrid_raid = «yes»
supportphoto="yes"
support_download="yes"
supportquota="yes"
supportitunes="yes"
supportddns="yes"
-- INSERT --
```

Добавляем `support_syno_hybrid_raid = «yes»` над строкою `supportphoto=«yes»`

```
192.168.1.184 - PuTTY
company_title="Synology"

# system options
timezone="Pacific"
language="def"
maillang="enu"
codepage="enu"
defquota="5"
defshare="public"
defgroup="users"
defright="writeable"
configured="no"
pswdprotect="no"
autoblock_exprieday="0"
autoblock_attempts="0"
autoblock_attempt_min="0"
support_syno_hybrid_raid = «yes»
supportphoto="yes"
support_download="yes"
supportquota="yes"
supportitunes="yes"
supportddns="yes"
#supportraidgroup = "yes"
-- INSERT --
```

Прокомментируйте следующую строку (поставьте перед строкой #):


`supportraidgroup = «yes»`

```
192.168.1.184 - PuTTY
support_hotspare="yes"
support_iscsi_btrfs_lun="yes"
support_iscsi_plugin="yes"
support_onsite_tool="yes"
support_ovs="yes"
support_performance_event="yes"
support_share_quota="yes"
support_share_snapshot="yes"
support_share_user_quota="yes"
support_spectre_meltdown_mitigation="yes"
support_sriov="yes"
support_ssd_cache="yes"
support_ssd_trim="yes"
support_trim="yes"
support_vaa1="yes"
support_webinstall="yes"
support_wol="yes"
support_write_cache="yes"
support_zram="yes"
supportraid="yes"
supportraidcross="yes"
#supportraidgroup="yes"
supportsystemtemperature="yes"
-- INSERT --
```

esc



:wq!


клавиша «ENTER» → Перезагрузите дисковую станцию и снова наслаждайтесь SHR. →
Основное меню → Диспетчер хранения → Раздел → Создать




Быстро → Далее

тип Raid → SHR → Далее







Btrfs → Далее



Применить





From:
<https://www.wwooss.ru/> - **worldwide open-source software**

Permanent link:
<https://www.wwooss.ru/doku.php?id=software:nas:shr>

Last update: **2025/02/01 09:49**

